

PT-EXL-EDL SERIES

Edge-Lit Exit Sign with Emergency Battery Back-up

Lage Lit Exit Sight With Efficigency Battery Back up

Catalog Number: Project Name: Note: Date: Type:

The PT-EXL-EDL Series is an edge-lit exit sign is a modern and sleek emergency signage solution. Instead of traditional backlighting, these signs utilize LED lights embedded along the edges of a transparent or mirrored acrylic panel, which illuminates the sign evenly. The PT-EXL-EDL series exit signs are often chosen for their minimalist appearance and their ability to blend seamlessly with various architectural styles while ensuring safety compliance.

Ideal use for commercial buildings, industrial facilities, entryways, stairways, and hallways.



CONSTRUCTION

Aluminum housing with high grade acrylic panel. Letter is 6" height with 3/4" stroke in bright Green. Removable directional indicators. Easy installation.

ELECTRICAL

Dual voltage operation with 120V/277VAC and input watt of 3.5W. Includes built-in 3.6V 600mAh Nickel cadmium battery with a 180-minute runtime and 24 hour charge time. Test switch and charge indicator.

MOUNTING

Aluminum mounting plate allows top, back or end mount.

LISTING

UL Listed, RoHS

WARRANTY

5 year limited warranty on electrical parts and housing. 3 year limited warranty on battery.










TECHNICAL SPECIFICATION

| INPUT WATT | 3.5W |
|---------------------|----------------------------|
| INPUT CURRENT | 0.027 - 0.013A |
| VOLTAGE | Dual Voltage 120V-277V |
| BATTERY TYPE | 3.6V 600mAh Nickel cadmium |
| EM RUN TIME | 180 mins |
| CHARGING TIME | 24 hrs |
| WORKING TEMPERATURE | 32°F ~ 104°F |
| IP RATING | Indoor Damp Location |

DIMENSION



ORDERING SAMPLE: PT-EXL-EDL-1-G-CLR-AL / PT-EXL-EDL-2-G-MIR-AL

| Model | Series/Style/Shape | Face | Letter | Finish | Housing | Mounting |
|-------|-----------------------|------|------------------|--------------|---------------|---------------------|
| EXIT | PT-EXL-EDL (Edge-lit) | 1 | G (Green) | CLR (Clear) | AL (Aluminum) | Ceiling, Wall, Side |
| EXIT | PT-EXL-EDL (Edge-lit) | 2 | | MIR (Mirror) | | |