

# PT-FLM2-MW-3CP

LED Mini Floodlight with CCT and Wattage Selector

Catalog Number:

Project Name:



optical control. The slim profile delivers enhanced lighting performance. Robust housing can withstand harsh outdoor environments.

The second generation FLM2 flood light series combines energy efficiency and advance

Available with knuckle mount or a u-bracket mount for convenient mounting option. Ideal use for facades, outdoor, signage, shopping centers, industrial areas and other outdoor places with spot lighting is needed.





Corrosion resistant die-cast aluminum housing with excellent heat management equipped for long lasting durability. Weather-proof gasketed that is IP65 rated. Small slim profile make it versatile for various different application.

#### ELECTRICAL

Luminaire is built with the highest quality driver that is Universal Voltage (120-277V), uses long lasting, high-efficient LED packages.

#### **OPTICAL SYSTEM**

Compact rugged glass lens is designed to reduce glace and improve overall lightdistribution through precision formed lens optics.

### **ENERGY SAVINGS**

Over 50% energy savings than traditionally fixtures, low heat productions requires less maintenance and operation cost.

FOR WET

#### LISTING

UL Listed, DLC Premium Listed, IP65 rated, RoHS

PREMIUM

WATTAGE	DELIVERED LUMENS	EFFICACY
40W	6,399	
50W	7,762	up to 165 lm/W
60W	9,229	

Based on IES results @ 4000K. Actual lumens may vary.

## TECHNICAL SPECIFICATION

CCT	3000K/4000K/5000K
CRI	70+
DIMMABLE	0-10V dimmable
PHOTOCELL	Photocell pre-installed
BEAM ANGLE	130°x130°
VOLTAGE	120V-277V
POWER FREQUENCY	50/60 Hz
POWER FACTOR	>0.9
WORKING TEMPERATURE	-40°F - +113°F
IP RATING	IP65 Wet Location
WARRANTY	5 year limited

ORDERING SAMPLE:	-		-	-	
Series	Wattage	CCT	Voltage	Mounting (Included)	Option
<b>PT-FLM2</b> Mini Flood Light	<b>MW</b> (40W/50W/60W)	<b>3CP</b> (3000K/4000K/5000K)	blank (120-277V)	K (1/2" Knuckle) U (U-bracket)	JB-FL



## PT-FLM2-MW-3CP

LED Mini Floodlight with CCT and Wattage Selector

Catalog Number:	Project Name:	Note:	Date:	Туре:	
-----------------	---------------	-------	-------	-------	--

## DIMENSION





U-Bracket Mount

QTY/CARTON

				(Knuckle a	nd U-bracket mo	ounting includ
CATALOG	А	В	C	D	E	F
PT-FLM2-MW-3CP	9"	8.27″	5.5"	1.81″	7.4″	1.8″



### CCT AND WATTAGE SELECTOR GUIDANCE



DIP Switch for Watt Control







#### DIP Switch for CCT & Photocell



JUNCTION BOX OPTION



**JB-FL** Floodlight Junction Box for Knuckle Mounting Option

