

PT-FLM2 SERIES

U-Bracket Mount

LED Mini Floodlight with CCT Selector

Catalog Number:	Project Name:	Note:	Date:	Туре:
optical control. The slim profile delivers e can withstand harsh outdoor environmer Available with knuckle mount or a u-brac	ket mount for convenient mounting option. hopping centers, industrial areas and other			

CONSTRUCTION

Corrosion resistant die-cast aluminum housing with excellent heat management equipped for long lasting durability. Weather-proof gasketed that is IP65 rated. Small slim profile make it versatile for various different application.

ELECTRICAL

Luminaire is built with the highest quality driver that is Universal Voltage (120-277V), uses long lasting, high-efficient LED packages.

OPTICAL SYSTEM

Compact rugged glass lens is designed to reduce glace and improve overall lightdistribution through precision formed lens optics.

ENERGY SAVINGS

Over 50% energy savings than traditionally fixtures, low heat productions requires less maintenance and operation cost.

FOR WET

LISTING

UL Listed, DLC Premium Listed, IP65 rated, RoHS

PREMIUM

WATTAGE	DELIVERED LUMENS	EFFICACY
	1,994 @ 3000K	
15W	2,135 @ 4000K	up to 150 lm/W
	2,064 @ 5000K	
30W	4,18 @ 3000K	
	4,442 @ 4000K	up to 153 lm/W
	4,341 @ 5000K	

Knuckle Mount

Based on IES results. Actual lumens may vary.

TECHNICAL SPECIFICATION

CRI	70+
DIMMABLE	0-10V dimmable
PHOTOCELL	Photocell pre-installed
BEAM ANGLE	130ºx130º
VOLTAGE	120V-277V
POWER FREQUENCY	50/60 Hz
POWER FACTOR	>0.9
WORKING TEMPERATURE	-40°F - +113°F
IP RATING	IP65 Wet Location
WARRANTY	5 year limited

ORDERING SAMPLE:	-		-	-	
Series	Wattage	CCT	Voltage	Mounting (Included)	Option
PT-FLM2 Mini Flood Light	15W	3CCT (3000K/4000K/5000K)	blank (120-277V)	K (1/2" Knuckle) U (U-bracket)	JB-FL
	30W				





PT-FLM2 SERIES

LED Mini Floodlight with CCT Selector

Catalog Number:	Project Name:	Note:	Date:	Туре:
-----------------	---------------	-------	-------	-------

DIMENSION





U-Bracket Mount

(Knuckle and U-bracket mounting included)

CATALOG	A	В	C	D	E	F
PT-FLM2-15W-3CCT	7.2″	5.24"	3.62″	1.81″	5″	1.77″
PT-FLM2-30W-3CCT	8"	6.3″	4.49"	1.81″	5.9"	1.65″







CCT SELECTOR GUIDANCE





DIP Switch for CCT & Photocell

JUNCTION BOX OPTION



JB-FL Floodlight Junction Box for Knuckle Mounting Option

www.portorlighting.com

2/2